


# Panasonic®



## Wide Plasma Display Operating Instructions

---

Model No. **TH-42PWD4**



Before connecting, operating or adjusting this product, please read these instructions completely. Please keep this manual for future reference.

English

# *Dear Panasonic Customer*

*Welcome to the Panasonic family of customers. We hope that you will have many years of enjoyment from your new Plasma Display.*

*To obtain maximum benefit from your set, please read these Instructions before making any adjustments, and retain them for future reference.*

*Retain your purchase receipt also, and note down the model number and serial number of your set in the space provided on the rear cover of these instructions.*

*Visit our Panasonic Web Site      <http://www.panasonic.co.jp/global/>*

## **Trademark Credits**

- VGA is a trademark of International Business Machines Corporation.
  - S-VGA is a registered trademark of the Video Electronics Standard Association.
- Even if no special notation has been made of company or product trademarks, these trademarks have been fully respected.

## **Note:**

Do not allow a still picture to be displayed for an extended period, as this can cause a permanent after-image to remain on the Plasma Display.  
Examples of still pictures include logos, video games, computer images, teletext and images displayed in 4:3 mode.

# Table of Contents

<b>Important Safety Notice</b> .....	<b>4</b>	<b>Surround Controls</b> .....	<b>25</b>
<b>Safety Precautions</b> .....	<b>5</b>	<b>Picture Adjustments</b> .....	<b>26</b>
<b>Accessories</b> .....	<b>7</b>	Advanced settings .....	27
Accessories Supply .....	7	<b>Setup for MULTI DISPLAY</b> .....	<b>28</b>
Optional Accessories .....	7	How to Setup MULTI DISPLAY .....	28
<b>Remote Control Batteries</b> .....	<b>8</b>	How to set the display location number for each Plasma Display ..	29
<b>Connections</b> .....	<b>9</b>	<b>Set up TIMER</b> .....	<b>30</b>
AV Input Terminals connection .....	10	PRESENT TIME Set .....	30
AV Out .....	11	TIMER Set .....	31
Component/RGB Input connection .....	12	<b>Screensaver (For preventing after-images)</b> .....	<b>32</b>
How to connect the PC Input Terminals .....	13	Setup of Screensaver Time .....	33
How to connect the Serial Terminals .....	14	Side Panel Adjustment .....	33
<b>Basic Controls</b> .....	<b>15</b>	<b>Setup for Input Signals</b> .....	<b>34</b>
<b>Power On/Off and input signal selection</b> .....	<b>16</b>	Component/RGB-in select .....	34
AC cord connection .....	16	3D Y/C Filter – For NTSC AV images .....	34
Power On/Off .....	16	Colour system / Panasonic Auto .....	35
Select the input signal .....	17	[Sync] .....	36
Selecting the On-Screen Menu Language .....	17	[Pull-in range] .....	36
<b>On screen Menu Display from Remote Control</b> .....	<b>18</b>	[Clamp position] .....	36
<b>ASPECT Controls</b> .....	<b>20</b>	[H-Freq. (kHz)/V-Freq. (Hz)] .....	36
<b>Adjusting Picture Pos./Size</b> .....	<b>22</b>	<b>Troubleshooting</b> .....	<b>37</b>
<b>Sound Adjustment</b> .....	<b>24</b>	<b>Specifications</b> .....	<b>38</b>
Mute .....	24		

# Important Safety Notice

**WARNING:** To prevent damage which may result in fire or shock hazard, do not expose this appliance to rain or moisture.

**Do not place containers with water (flower vase, cups, cosmetics, etc.) above the set. (including on shelves above, etc.)**

**WARNING:** 1) To prevent electric shock, do not remove cover. No user serviceable parts inside. Refer servicing to qualified service personnel.

2) Do not remove the earthing pin on the power plug. This apparatus is equipped with a three pin earthing-type power plug. This plug will only fit an earthing-type power outlet. This is a safety feature. If you are unable to insert the plug into the outlet, contact an electrician.

Do not defeat the purpose of the earthing plug.

## **WARNING**

This is a class A product. In a domestic environment this product may cause radio interference in which case you may be required to take adequate measures.

## **CAUTION**

This appliance is intended for use in environments which are relatively free of electromagnetic fields.

Using this appliance near sources of strong electromagnetic fields or where electrical noise may overlap with the input signals could cause the picture and sound to wobble or cause interference such as noise to appear.

To avoid the possibility of harm to this appliance, keep it away from sources of strong electromagnetic fields.

To prevent electric shock, ensure the grounding pin on the AC cord power plug is securely connected.

# Safety Precautions

## WARNING

### Setup

This Plasma Display is for use only with the following optional accessories. Use with any other type of optional accessories may cause instability which could result in the possibility of injury.

(All of the following accessories are manufactured by Matsushita Electric Industrial Co., Ltd.)

- Speakers ..... TY-SP42PWD3W
- Pedestal ..... TY-ST42PT3-K
- Wall stand ..... TY-ST42PW1
- Mobile stand ..... TY-ST42PF3
- Wall-hanging bracket (vertical) ..... TY-WK42PV1
- Wall-hanging bracket (angled) ..... TY-WK42PR1
- Ceiling unit ..... TY-CE42PS1
- Terminal cover ..... TY-UPS200

Always be sure to ask a qualified technician to carry out set-up.

**Do not place the Plasma Display on sloped or unstable surfaces.**

- The Plasma Display may fall off or tip over.

**Do not place any objects on top of the Plasma Display.**

- If water is spilled onto the Plasma Display or foreign objects get inside it, a short-circuit may occur which could result in fire or electric shock. If any foreign objects get inside the Plasma Display, please consult your local Panasonic dealer.

**If using the pedestal (optional accessory), leave a space of at least 10 cm at the top, left and right, at least 6 cm at the bottom, and at least 7 cm at the rear. If using some other setting-up method, leave a space of at least 10 cm at the top, bottom, left and right, and at least 1.9 cm at the rear.**

### When using the Plasma Display

The Plasma Display is designed to operate on 220 - 240 V AC, 50/60 Hz.

**Do not cover the ventilation holes.**

- Doing so may cause the Plasma Display to overheat, which can cause fire or damage to the Plasma Display.

**Do not stick any foreign objects into the Plasma Display.**

- Do not insert any metal or flammable objects into the ventilations holes or drop them onto the Plasma Display, as doing so can cause fire or electric shock.

**Do not remove the cover or modify it in any way.**

- High voltages which can cause severe electric shocks are present inside the Plasma Display. For any inspection, adjustment and repair work, please contact your local Panasonic dealer.

**Securely insert the power cord plug as far as it will go.**

- If the plug is not fully inserted, heat may be generated which could cause fire. If the plug is damaged or the wall socket plate is loose, they shall not be used.

**Do not handle the power cord plug with wet hands.**

- Doing so may cause electric shocks.

**Do not do anything that may damage the power cable. When disconnecting the power cable, pull on the plug body, not the cable.**

- Do not damage the cable, make any modifications to it, place heavy objects on top of it, heat it, place it near any hot objects, twist it, bend it excessively or pull it. To do so may cause fire and electric shock. If the power cable is damaged, have it repaired at your local Panasonic dealer.

**If the Plasma Display is not going to be used for any prolonged length of time, unplug the power cord plug from the wall outlet.**

# Safety Precautions

---

## If problems occur during use

**If a problem occurs (such as no picture or no sound), or if smoke or an abnormal odour starts to come out from the Plasma Display, immediately unplug the power cord plug from the wall outlet.**

- If you continue to use the Plasma Display in this condition, fire or electric shock could result. After checking that the smoke has stopped, contact your local Panasonic dealer so that the necessary repairs can be made. Repairing the Plasma Display yourself is extremely dangerous, and shall never be done.

**If water or foreign objects get inside the Plasma Display, if the Plasma Display is dropped, or if the cabinet becomes damaged, disconnect the power cord plug immediately.**

- A short circuit may occur, which could cause fire. Contact your local Panasonic dealer for any repairs that need to be made.

## CAUTION

## When using the Plasma Display

**Do not bring your hands, face or objects close to the ventilation holes of the Plasma Display.**

- Heated air comes out from the ventilation holes at the top of Plasma Display will be hot. Do not bring your hands or face, or objects which cannot withstand heat, close to this port, otherwise burns or deformation could result.

**Be sure to disconnect all cables before moving the Plasma Display.**

- If the Plasma Display is moved while some of the cables are still connected, the cables may become damaged, and fire or electric shock could result.

**Disconnect the power cord plug from the wall socket as a safety precaution before carrying out any cleaning.**

- Electric shocks can result if this is not done.

**Clean the power cable regularly to prevent it becoming dusty.**

- If dust built up on the power cord plug, the resultant humidity can damage the insulation, which could result in fire. Pull the power cord plug out from the wall outlet and wipe the mains lead with a dry cloth.

## Cleaning and maintenance

**The front of the display panel has been specially treated. Wipe the panel surface gently using only a cleaning cloth or a soft, lint-free cloth.**

- If the surface is particularly dirty, wipe with a soft, lint-free cloth which has been soaked in pure water or water to which a small amount of neutral detergent has been added, and then wipe it evenly with a dry cloth of the same type until the surface is dry.
- Do not scratch or hit the surface of the panel with fingernails or other hard objects, otherwise the surface may become damaged. Furthermore, avoid contact with volatile substances such as insect sprays, solvents and thinner, otherwise the quality of the surface may be adversely affected.

**If the cabinet becomes dirty, wipe it with a soft, dry cloth.**

- If the cabinet is particularly dirty, soak the cloth in water to which a small amount of neutral detergent has been added and then wring the cloth dry. Use this cloth to wipe the cabinet, and then wipe it dry with a dry cloth.
- Do not allow any detergent to come into direct contact with the surface of the Plasma Display. If water droplets get inside the unit, operating problems may result.
- Avoid contact with volatile substances such as insect sprays, solvents and thinner, otherwise the quality of the cabinet surface may be adversely affected or the coating may peel off. Furthermore, do not leave it for long periods in contact with articles made from rubber or PVC.


# Accessories

## Accessories Supply


Check that you have the accessories and items shown




Operating Instruction book




Remote Control Transmitter  
EUR646525




Batteries for the Remote  
Control Transmitter  
(2 × R6 Size)




AC cord



Fixing bands  
TMME187 × 2




Ferrite core  
J0KF00000018 × 2



## Optional Accessories


● Speakers  
TY-SP42PWD3W




● Pedestal  
TY-ST42PT3-K




● Wall stand  
TY-ST42PW1




● Mobile stand  
TY-ST42PF3




● Wall-hanging bracket  
(vertical)  
TY-WK42PV1




● Wall-hanging bracket  
(angled)  
TY-WK42PR1



● Ceiling unit  
TY-CE42PS1



● Terminal cover  
TY-UPS200




### For assembling

Full instructions are supplied with each optional accessory for use with this Plasma Display.

# Remote Control Batteries

## Requires two R6 batteries.

1. Turn the transmitter face down. Press and slide off the battery cover.
2. Install the batteries as shown in the battery compartment. (Polarity + or – must match the markings in the compartment).
3. Replace the cover and slide in reverse until the lock snaps.



### Helpful Hint:

For frequent remote control users, replace old batteries with Alkaline batteries for longer life.

### ⚠ Precaution on battery use


Incorrect installation can cause battery leakage and corrosion that will damage the remote control transmitter.

#### Observe the following precaution:

1. Batteries shall always be replaced as a pair. Always use new batteries when replacing the old set.
2. Do not combine a used battery with a new one.
3. Do not mix battery types (example: "Zinc Carbon" with "Alkaline").
4. Do not attempt to charge, short-circuit, disassemble, heat or burn used batteries.
5. Battery replacement is necessary when remote control acts sporadically or stops operating the Plasma Display set.



# Connections

When connecting the speakers, be sure to use only the optional accessory speakers. Refer to the speaker's Installation Manual for details on speaker installation.



**– Cable fixing bands**

Secure any excess cables with bands as required.




- AV IN Terminals  
(see page 10, 11)
- COMPONENT/RGB IN and Audio  
IN Terminals (see page 12)
- From EXIT monitor Terminal  
on Computer (see page 13)
- From SERIAL Terminal on  
Computer (see page 14)


## AV Input Terminals connection

Connect the signal source equipment.

(Example) When connecting an S VIDEO VCR




### VIDEO signal connection



**Note:**

Additional equipment and cables shown are not supplied with this set.


(Example) When connecting 21 pin scart cables.



**Notes:**


- (1) Additional equipment, cables and an adapter plug shown are not supplied with this set.
- (2) 21 pin connectors and 21 pin scart plugs are connectors used in Europe.

## AV Out



## Component/RGB Input connection


### Component signals (Y, P<sub>B</sub>, P<sub>R</sub>) connection



**Notes:**

- (1) Change the “Component/RGB-in” setting in the “Setup” menu to “Y/P<sub>B</sub>/P<sub>R</sub>”. (see page 34, 36)
- (2) Additional equipment, cables and adapter plugs shown are not supplied with this set.


### RGB signal (R, G, B, HD, VD) connection




**Notes:**

- (1) Change the “Component/RGB-in” setting in the “Setup” menu to “RGB”. (see page 34, 36)
- (2) Additional equipment, cables and adapter plugs shown are not supplied with this set.

# How to connect the PC Input Terminals




### Installing the ferrite core



### Notes:

- (1) Computer signals which can be input are those with a horizontal scanning frequency of 15.5 to 110 kHz and vertical scanning frequency of 48 to 120 Hz. (However, signals cannot be displayed if signals exceeding 1200 lines will not be displayed properly.)
- (2) The display resolution is a maximum 640 × 480 dots when the aspect mode is set to "4:3", and 852 × 480 dots when the aspect mode is set to "16:9". If the display resolution exceeds these maximums, it may not be possible to show fine detail with sufficient clarity.
- (3) The PC input terminals are DDC1/2B-compatible. If the computer being connected is not DDC1/2B-compatible, you will need to make setting changes to the computer at the time of connection.
- (4) Some PC models cannot be connected to the set.
- (5) There is no need to use an adapter for computers with DOS/V compatible D-sub 15P terminal.
- (6) The computer shown in the illustration is for example purposes only.
- (7) Additional equipment and cables shown are not supplied with this set.
- (8) Do not set the horizontal and vertical scanning frequencies for PC signals which are above or below the specified frequency range.

### Signal Names for D-sub 15P Connector




Pin Layout for PC Input Terminal

Pin No.	Signal Name	Pin No.	Signal Name	Pin No.	Signal Name
①	R	⑥	GND (Ground)	⑪	GND (Ground)
②	G	⑦	GND (Ground)	⑫	SDA
③	B	⑧	GND (Ground)	⑬	HD/SYNC
④	GND (Ground)	⑨	NC (not connected)	⑭	VD
⑤	GND (Ground)	⑩	GND (Ground)	⑮	SCL

## How to connect the SERIAL Terminals

The SERIAL terminal is used when the Plasma Display is controlled by a computer.



### Notes:

- (1) Use the RS-232C cable to connect the computer to the Plasma Display.
- (2) The computers shown is for example purposes only.
- (3) Additional equipment and cables shown are not supplied with this set.

The SERIAL terminal conforms to the RS-232C interface specification, so that the Plasma Display can be controlled by a computer which is connected to this terminal.

The computer will require software which allows the sending and receiving of control data which satisfies the conditions given below. Use a computer application such as a programming language to software. Refer to the documentation for the computer application for details.


### Communication parameters

Signal level	RS-232C compliant
Synchronization method	Asynchronous
Baud rate	9600 bps
Parity	None
Character length	8 bits
Stop bit	1 bit
Flow control	—

RS-232C Conversion cable	
D-sub 9-pin female	Details
②	R X D
③	T X D
⑤	GND
④ ⑥	Non use
⑦	Shorted
⑧	
① • ⑨	NC

### Basic format for control data

The transmission of control data from the computer starts with a STX signal, followed by the command, the parameters, and lastly an ETX signal in that order. If there are no parameters, then the parameter signal does not need to be sent.



### Notes:


- (1) If multiple commands are transmitted, be sure to wait for the response for the first command to come from this unit before sending the next command.
- (2) If an incorrect command is sent by mistake, this unit will send an "ER401" command back to the computer.

### Command

Command	Parameter	Control details
PON	None	Power ON
POF	None	Power OFF
AVL	**	Volume 00 - 63
AMT	0	Audio mute OFF
	1	Audio mute ON
IIS	None	Input select (toggle)
	VID	AV Mode
	YP1	Component / RGB mode (processed as a Y/Pb/Pr or RGB signals as set by this unit)
	RG1	PC Mode
DAM	None	Screen mode select (toggle)
	NORM	4 : 3
	ZOOM	Zoom
	FULL	16 : 9
	JUST	Just
	SELF	Panasonic Auto

With the power off, this display responds to PON command only.

# Basic Controls



## Main Power On/Off Switch

### Power Indicator

The Power Indicator will light.

- Power-OFF ..... Indicator not illuminated (The unit will still consume some power as long as the power cord is still inserted into the wall outlet.)
- Stand-by  $\phi$  .... Red
- Power-ON ..... Green

## INPUT button

### (AV (S Video)/Component, RGB/PC Mode Selection)

Push the "INPUT" button to select AV(S Video)/Component or RGB/PC input signal modes sequentially. (see page 17)

## Volume Adjustment


Push the Volume Up "+" or Down "-" button to increase or decrease the sound volume level.

## Stand-by (ON/OFF) button

The Plasma Display must first be plugged into the wall outlet and turned on at the power switch (see page 16). Push this button to turn the Plasma Display On, from Standby mode. Push it again to turn the Plasma Display Off to Standby mode.

## Status button

Push the "Status" button to display the current system status.



- ① AV(S Video)/Component, RGB/PC mode
  - ② Aspect mode (see page 20)
  - ③ Off timer
- The off timer indicator is displayed only when the off timer has been set.

## N button

(see page 23, 24, 26, 27)

## PICTURE button

(see page 26)

## PICTURE POS./SIZE button

(see page 22)

## PC button

Push the "PC" mode selection button to select the PC mode. This button is used to switch directly to PC mode.

## SURROUND button

(see page 25)

## INPUT button (AV(S Video)/Component, RGB/PC Mode Selection)

Press to select AV(S Video)/Component or RGB/PC input signal modes sequentially. (see page 17)

## Sound mute On/Off (see page 24)

## Volume Adjustment

Press the Volume Up "+" or Down "-" button to increase or decrease the sound volume level.

## R button

## ACTION button

Press to make selections

## POSITION buttons

## SET UP button (see page 18)

## SOUND button (see page 24)

## ASPECT button


Press to adjust the aspect. (see page 20)

## OFF TIMER button

The Plasma Display may be preset to switch to stand-by after a fixed period. The setting changes to 30 minutes, 60 minutes, 90 minutes and 0 minutes (off timer cancelled) each time the button is pressed.

When three minutes remain, "Off timer 3" will flash.


The off timer is cancelled if a power interruption occurs.




# Power On/Off and input signal selection

## AC cord connection

Connecting the AC cord plug to the Plasma Display.



## Power On/Off



### Connecting the plug to the Wall Outlet

#### Note:

Main plug types vary between countries. The power plug shown at left may, therefore, not be the type fitted to your set.

Push the Power switch on the Plasma Display to turn the set on Power-On

Power Indicator: Green

Example: The screen below is displayed for a while after the Plasma Display is turned on. (setting condition is an example.)



When the Power is turned on for the first time, the Language selection screen is displayed.


From the second time on, language selection can be done from the setup menu. (see page 17)

Select the desired language using the ▲ and ▼ keys and press the Action button.




From the second time on, the below screen is displayed for a while (setting condition is an example).




Press the  button on the remote control to turn the Plasma Display off




Power Indicator: Red (standby)

Press the  button on the remote control to turn the Plasma Display on

Power Indicator: Green

Turn the power to the Plasma Display set off by pressing the  switch on the Plasma Display, when the Plasma Display is on or in standby mode.


## Select the input signal



Press the INPUT button to select the input AV signal desired from equipment such as a VCR which has been connected to the Plasma Display.

Input signals will change as follows:

For Component Input (see page 34)





For RGB Input (see page 34)



## Selecting the On-Screen Menu Language



Press to display the Set Up menu.




Press to select the OSD Language.

Press to select your preferred language.


selectable languages

- English(UK)
- Deutsch
- Français
- Italiano
- Español
- ENGLISH(US)
- 中文 .....(Chinese)




# On-Screen Menu Display from Remote Control


To Picture adjust menu  
(see page 26)



To Advanced Settings  
(see page 26, 27)




To Sound adjust menu  
(see page 24)




To Picture Pos./Size adjust menu  
(see page 22)







During "AV" and "Component"  
input signal modes.




During "RGB" and "PC"  
input signal modes.




Press to select each item.



# On-Screen Menu Display from Remote Control




Press to access each adjust screen.




Press the R button to return to "Setup" menu.


To Signal screen for AV (see page 35)




To Signal screen for RGB (see page 36)



To Signal screen for Component (see page 36)





To Signal screen for PC (see page 36)



**Note:**

"Signal" setup menu displays different setting condition for each input signals. (see page 17)

To setup Screensaver (see page 32)







Press to select each time adjust screen.


Press to display each adjust screen.




Press the R button to return to "Screensaver" menu.




To setup Multidisplay screen (see page 28)




To Set up Timer selection screen (see page 30)






Press to select each Timer adjustment items.



When select Timer adjustment item, press this button to Set up TIMER screen.



Press the R button to return to "Setup" menu.




# ASPECT Controls

The Plasma Display will allow you to enjoy viewing the picture at its maximum size, including wide screen cinema format picture.




## ASPECT button






The aspect mode changes each time the ASPECT button is pressed.



## Notes:

- (1) During RGB and PC input signal modes, the mode switches between "4:3", "Zoom" and "16:9" only.
- (2) For a 525p (480p) signal input during "Component" input signal mode, the mode switches between "Zoom" and "16:9" only.
- (3) For a 1125i (1080i), 750p (720p) signal input during "Component" input signal mode, the mode is set to "16:9" mode, and switching is not possible.  
For a 525i (480i), 625i (575i) signal input during "Component" input signal mode, "Panasonic Auto" can not be selected.
- (4) The aspect mode is memorized separately for each input terminal (AV, Component, RGB and PC).



Mode	Picture	Explanation
4 : 3		4:3 will display a 4:3 picture at its standard 4:3 size.
Zoom		Zoom mode magnifies the central section of the picture.
16 : 9		16:9 will display the picture at its maximum size but with sight elongation.
Just		Just mode will display a 4:3 picture at its maximum size but with aspect correction applied to the center of the screen so that elongation is only apparent at the left and right edges of the screen. The size of the picture will depend on the original signal.
Panasonic Auto	 <p>For an elongated image Image is expanded</p> <p>For a 4:3 image</p> <p>Changes in accordance with the Panasonic Auto mode setting (see page 35)</p>	<p>The display will automatically become enlarged (depending on the picture source), allowing you to view the picture at its maximum size.</p> <p><b>Note:</b> Panasonic Auto mode is designed to automatically adjust the aspect ratio to handle a mix of 16:9 and 4:3 program material. Certain 4:3 program material, such as stock market data screens, may occasionally cause the image size to change unexpectedly. When viewing such programs, it is recommended that the ASPECT be set to 4:3.</p>

**Notes:**

- (1) Do not allow 4:3 mode to be displayed for an extended period, as this can cause a permanent after-image to remain on the Plasma Display Panel.
- (2) The S Video terminal on this set can detect specially encoded signals that are compatible with a wide screen monitor. When a full image from the S Video terminal of specially encoded video is detected by the set, the screen size is automatically set to 16:9 mode.

# Adjusting Picture Pos./Size

## Adjusting screen

1



ASPECT


Press to select the screen mode to adjust.

2

PICTURE  
POS./SIZE




Press to display the Picture Pos./Size menu.




Press to select H-Pos/H-Size/V-Pos/V-Size/Clock Phase.


During "AV" and "Component" input signal modes.



During "RGB" and "PC" input signal modes.




3



Press to adjust screen/position.











Press to exit from adjust mode.




### Notes:

- (1) Adjustment details are memorized separately for different input signal formats (Adjustments for component signals are memorized for 525i (480i), 625i (575i), 525p (480p), 1125i (1080i) and 625p (575p), 750p (720p) each, and RGB/PC signals are memorized for each frequency.)
- (2) If a "Cue" or "Rew" signal from a VCR or DVD player is received, the picture position will shift up or down. This picture position movement cannot be controlled by the Picture Pos./Size function.

<p style="text-align: center;"><b>H-Pos</b></p>	<p>When the Position Left “◀” button is pressed.</p> 	<p>When the Position Right “▶” button is pressed.</p> 
<p style="text-align: center;"><b>H-Size</b></p>	<p>When the Position Left “◀” button is pressed.</p> 	<p>When the Position Right “▶” button is pressed.</p> 
<p style="text-align: center;"><b>V-Pos</b></p>	<p>When the Position Left “◀” button is pressed.</p> 	<p>When the Position Right “▶” button is pressed.</p> 
<p style="text-align: center;"><b>V-Size</b></p>	<p>When the Position Left “◀” button is pressed.</p> 	<p>When the Position Right “▶” button is pressed.</p> 
<p><b>Clock Phase (RGB/PC in Mode)</b></p>	<p>Flickering and distortion can be eliminated by using the Position Left “◀” or Right “▶” button to carry out adjustment.</p>	




## Helpful Hint ( / Normalisation )


While the Picture Pos./Size display is active, if either the N button on the remote control is pressed at any time or the  (Action button) is pressed during “Normalise”, then all adjustment values are returned to the factory settings.

# Sound Adjustment

**1**  Press to display the Sound menu.

**2** Select to adjust each item.

 Press to select the desired adjustment menu.  
Select the desired level by listening to the sound.




**Bass**  
Adjusts low sounds

**Treble**  
Adjusts high sounds

**Balance**  
Adjusts left and right volumes

**Surround** (see next page)  
Select On or Off




Normal Emits the original sound.



Auto Automatically controls proper volume level.


• To end adjustments

 Press the R button

**Note:**


Press the SURROUND button to directly turn the surround effect On and Off. (see next page)

## Helpful Hint ( / Normalisation )

While the "Sound" menu is displayed, if either the N button on the remote control is pressed at any time or the  (Action button) is pressed during "Normalise", then all adjustment values are returned to the factory settings.

## Mute

Useful when answering the phone or receiving unexpected visitors.

 Press this button to mute the sound.  
Press again to reactivate sound. Sound is also reactivated when power is turned off or volume level is changed.

# Surround Controls




## SURROUND Button

The benefits of surround sound are enormous. You can be completely enveloped in sound; just as if you were at a concert hall or cinema.


The surround setting switches on and off each time the SURROUND button is pressed.

On  $\longleftrightarrow$  Off




### Note:


The surround settings are memorized separately for each Sound mode (Auto, Normal).





# Picture Adjustments


**1**  Press the PICTURE button on the Remote Control to display the Picture menu.

**2** Select to adjust each item.

 Press to select the menu to adjust.  
Select the desired level by looking at the picture behind the menu.



Press the left ◀ or right ▶ button to switch between modes.



### Normal

For viewing in standard (evening lighting) environments.

This menu selects the normal levels of Brightness and Contrast.

### Dynamic

For viewing in brighter environments.

This menu selects higher than normal levels of Brightness and Contrast.

### Cinema


Ideal for movies.

- Can be selected for AV/Component.

### Note:


If you would like to change the picture and colour of the selected Picture menu to something else, adjust using the items in the Picture menu. (see next page)

Press the left ◀ or right ▶ button to select "ON". Press the down ▼ button to enter Advanced Settings mode. Advanced Settings ON Enables fine picture adjustment at a professional level (see next page).




Advanced Settings Off Displays images with settings of the Picture menu.

Press the left ◀ or right ▶ button to switch between modes.



## Helpful Hint ( / Normalisation )

While the "Picture" menu is displayed, if either the N button on the remote control is pressed at any time or the  (Action button) is pressed during "Normalise", then all adjustment values are returned to the factory settings.

Item	Effect	Adjustments
Contrast	Less     More	Selects the proper brightness and density for the room.
Brightness	Darker     Brighter	Adjusts for easier viewing of dark pictures such as night scenes and black hair.
Colour	Less     More	Adjusts slightly to a lighter colour.
Tint (NTSC only)	Reddish     Greenish	Adjust for nice skin colour.
Sharpness	Less     More	Displays a sharp image.

**Notes:**

- (1) "Colour", "Tint" and "Sharpness" settings cannot be adjusted for "RGB" and "PC" input signal modes.
- (2) You can change the level of each function (Contrast, Brightness, Colour, Tint, Sharpness) for each Picture menu.
- (3) The setting details for normal, dynamic and cinema respectively are memorized separately for each input mode (AV, Component, RGB).
- (4) The "Tint" setting can be adjusted for NTSC signal only.

**Note:**

There is little change when Picture is increased with a bright picture or reduced with a dark picture.

## Advanced Settings

Item	Effect	Details
Black extension	Less     More	Adjusts the dark shades of the image in gradation.
W/B High R	Less     More	Adjusts the white balance for light red areas.
W/B High B	Less     More	Adjusts the white balance for light blue areas.
W/B Low R	Less     More	Adjusts the white balance for dark red areas.
W/B Low B	Less     More	Adjusts the white balance for dark blue areas.
Gamma	Down     Up	2.0 ↔ 2.2 ↔ 2.5

**Notes:**

- (1) Carry out "W/B" adjustment as follows.
  - Ⓐ Adjust the white balance of the bright sections using the "W/B High R" and "W/B High B" settings.
  - Ⓑ Adjust the white balance of the dark sections using the "W/B Low R" and "W/B Low B" settings.
  - Ⓒ Repeat steps Ⓐ and Ⓑ to adjust.
 Steps Ⓐ and Ⓑ affect each other's settings, so repeat each step in turn to make the adjustment.
- (2) The adjustment values are memorized separately for each input mode (AV, Component, RGB and PC).
- (3) The adjustment range values should be used as an adjustment reference.



## Helpful Hint ( / Normalisation )

On the remote control unit, while the "Advanced settings" menu is displayed, if either the N button is pressed at any time or the (Access button) is pressed during "Normalise", then all adjustment values are returned to the factory settings.

# Setup for MULTI DISPLAY

- ① By lining up Plasma Displays in groups of 4 or 9 as illustrated below, an enlarged picture may be displayed across all screens.
- ② For this mode of operation, each plasma display has to be set up with a Display number to determine its location.

group of 4 (2x2)



group of 9 (3x3)




## How to Setup MULTI DISPLAY

1




Press to display the Setup menu screen.

2




Press to select the MULTI DISPLAY Setup.

Press to the "MULTI DISPLAY Setup" menu.




3



Press to select the MULTI DISPLAY Setup.


Press to "On" or "Off".

Press to store the above Setup.



## How to set the display location number for each Plasma Display

**4**




Press to select Ratio (2nd step).

Press to select "2x2", "3x3".

MULTI DISPLAY Setup	
MULTI DISPLAY Setup	On
Ratio	2 X 2
Location	A1

**5**



Press to select Location.

Press to select the required arrangement number. (A1-C3 : Refer to the following)


MULTI DISPLAY Setup	
MULTI DISPLAY Setup	On
Ratio	2 X 2
Location	A1

Display Number locations for each arrangement

A1	A2
B1	B2

A1	A2	A3
B1	B2	B3
C1	C2	C3

**6**



Press twice to exit from Setup.

**Notes:**


- For PC or RGB input signals, normal multi-display magnification is only available at the VGA resolution.
- The multi-display capability is not functional for component signals.


# Set up TIMER


The timer can switch the Plasma Display On or Off.


Before attempting Timer Set, confirm the PRESENT TIME and adjust if necessary. Then set POWER ON Time / POWER OFF Time.

Display the Set up TIMER screen



**1**  Press to display the Setup menu screen.

**2**  Press to select Set up TIMER.


 Press to display the Set up TIMER screen.


Setup
Component/RGB-in select
Signal
Screensaver
OSD Language
MULTI DISPLAY Setup
Set up TIMER

Set up TIMER
PRESENT TIME
POWER ON Function
POWER ON Time
POWER OFF Function
POWER OFF Time


## PRESENT TIME Set


To set up PRESENT TIME, follow the procedure described below.

**1**  Press to select PRESENT TIME.


 Press to display the PRESENT TIME Setting screen.

PRESENT TIME Setup
PRESENT TIME
Hours Adjustment
Minutes Adjustment

**2**  Press to select Hours Adjustment / Minutes Adjustment.

 Press to set up Hours or Minutes


- ▶ button: Forward
- ◀ button: Back

 Press to store PRESENT TIME Setup.

PRESENT TIME Setup
PRESENT TIME
Hours Adjustment
Minutes Adjustment

## TIMER Set

1




Press to select  
POWER ON Time/POWER OFF Time.

Set up TIMER	
PRESENT TIME	0:52
POWER ON Function	Off
POWER ON Time	0:00
POWER OFF Function	Off
POWER OFF Time	0:00

Press to display the POWER ON  
Setup / POWER OFF Setup  
screen.

2



Press to select Hours Adjustment/  
Minutes Adjustment.


Press to adjust each time.

POWER ON Setup	
POWER ON Time	0:52
Hours Adjustment	00
Minutes Adjustment	52

Press to complete POWER ON Time  
/ POWER OFF Time and return to  
the Set up TIMER screen.

POWER OFF Setup	
POWER OFF Time	0:00
Hours Adjustment	00
Minutes Adjustment	00

3




Press to select POWER ON  
Function/POWER OFF Function.

Press to select On.

Press to store setting.

Set up TIMER	
PRESENT TIME	0:52
POWER ON Function	On
POWER ON Time	0:00
POWER OFF Function	On
POWER OFF Time	0:00

4




Press twice to exit from Setup.


**Note:**


Timer function will not work unless "PRESENT TIME" is set.

# Screensaver (For preventing after-images)


Do not display a still picture, especially in 4:3 mode, for any length of time.  
If the display must remain on, a Screensaver should be used.


**1**  Press to display the Setup menu screen.

**2**  Press to select the Screensaver.  
Press to select the Screensaver screen.






## Reversal / Scroll selection


**3**  Press to select the Function.  
Press to select the desired function.  
Image Reversal ↔ White bar scroll  
Image Reversal : Negative image will be displayed on the screen.  
White bar scroll : The white bar will scroll from left to right.





## Mode selection

**4**  Press to select the Mode.  
Press to select each mode items.

- Off
- Interval : Operates when Periodic Time and Operating Time are setup and those times arrive.
- Time Designation : Operates when Start Time and Finish Time are setup and those times arrive.
- On : Operates when the  (Action) is pressed.  
If the Mode is at On, the menu screen will disappear and the Screensaver will be activated.  
**To stop the Screensaver under On, press the  button.**




After selecting Time Designation or Interval, the relevant Time Setup will become available for selection and the Operating Time may be set.





## Setup of Screensaver Time


5



Press to select Start Time/ Finish Time (When Time Designation is selected).  
 Press to select Periodic Time/ Operating Time (When Interval is selected).  
 Press to select each Time Adjustment screen.



6




Press to select Hours Adjustment/ Minutes Adjustment.  
 Press to Setup Hours or Minutes.  
 ▶ button: Forward  
 ◀ button: Back  
 Press to store settings.

**Note:** Timer function will not work unless "PRESENT TIME" is set.

## Side Panel Adjustment


Do not display a picture in 4:3 mode for an extended period, as this can cause an after-image to remain on the side panels either side of the display field. To prevent the appearance of such an after-image, illuminate the side panels.




1

To display the Screensaver screen.  
 (Refer to the previous page, operation guide steps 1 and 2)

2



Press to select the SP Adjustment.  
 Press to select Low, Mid, High.



Off ↔ Low ↔ Mid ↔ High

3



Press to exit from Screensaver.

**Notes:**

- Setting the side panel to High mode for an extended period may result in occurrence of after-images.
- The side panels may flash (alternate black/white) depending on the picture being shown on the screen. In such an occurrence, use the Cinema mode.


# Setup for Input Signals

## Component/RGB-in Select

Select to match the signals from the source connected to the Component/RGB input terminals.

Y, P<sub>B</sub>, P<sub>R</sub> signals ⇒ “Component”

R, G, B, HD, VD signals ⇒ “RGB”




1




Press to display the Setup menu screen.

2



Press to select the “Component/RGB-in select”.

Press to select the desired mode.




Component ↔ RGB



Press to exit from adjust mode.

## 3D Y/C Filter – For NTSC video images

Select “Signal” from the “Setup” menu during AV input signal mode. (“Signal [AV]” menu is displayed.)





Press to select the “3D Y/C Filter (NTSC)”


Press to set On/Off.



Press to exit from adjust mode.



Press  (Action) button




### Note:

When on, this setting only affects NTSC input signals.


## Colour system / Panasonic Auto

Select Signal from the "Setup" menu during AV (S Video) input signal mode. ("Signal [AV]" menu is displayed.)



Press to select the "Colour System" or "Panasonic Auto".


Press to select each functions.



↓ Press (Action) button

### If the picture image becomes unstable:


With the system set on Auto, under conditions of low level or noisy input signals the image may in rare cases become unstable. Should this occur, set the system to match the format of the input signal.






Mode	Function
Colour system	Set the colour system to match the input signal. If set to "Auto", the colour system is determined automatically. <div style="text-align: center;"> <span style="border: 1px solid black; padding: 2px;">                     &gt; Auto &lt;-&gt; PAL &lt;-&gt; SECAM &lt;-&gt; M.NTSC &lt;-&gt; NTSC &lt;                 </span> </div>
Panasonic Auto (4:3)	Set to "4 : 3" to view 4:3 images in an unchanged format when Panasonic Auto is selected. If you would like to view 4:3 images in "Just" format, set to "Just".

# Setup for Input Signals

Select Signal from the "Setup" menu during RGB or PC input signal mode.



The following operation methods are the same for both the Signal [RGB] and Signal [PC].




## Sync

### Setting RGB sync signal:

Confirm that the input is set to RGB INPUT (this setting is valid only for RGB INPUT).

- H&V: The H and V sync signals are input from the HD/VD connector.
- on G: Uses a synchronized signal on the Video G signal, which is input from the G connector.
- on VIDEO: Compatible with the scart plug (Europe)  
The composite video signal input from the VIDEO input terminal is used by dividing the sync signals.



### Setting PC sync signal:


Confirm that the input is set to PC INPUT (this setting is valid only for PC INPUT).

- H&V: The H and V sync signals are input from the HD/VD connector.
- on G: Uses a synchronized signal on the Video G signal, which is input from the G connector.

## Pull-in range

Sets the width for different frequencies.

(This setting is the same for both Signal [RGB] and Signal [PC].)



## Clamp position

Adjusts the clamp position.

The following operation methods are the same for "Signal" menu during Component, RGB and PC input signal mode. Normally, these adjustments are set to appropriate levels and therefore, do not need to be altered.


## H-Freq (kHz)/V-Freq (Hz)

Displays the H (Horizontal)/V (Vertical) frequencies.

This display is valid only for RGB input and PC input.











Display range:

- Horizontal 15.5 - 110 kHz
- Vertical 48 - 120 Hz




# Troubleshooting

Before you call for service, determine the symptoms and make a few simple checks as shown below.


Symptoms		Checks
Picture	Sound	
 <p>Interface</p>	 <p>Noisy Sound</p>	Electrical Appliances Cars/Motorcycles Fluorescent light
 <p>Normal Picture</p>	 <p>No Sound</p>	Volume (Check whether the mute function has been activated on the remote control.)
 <p>No Picture</p>	 <p>No Sound</p>	Not plugged into AC outlet Not switched on Picture and Brightness/Volume setting (Check by pushing the power switch or stand-by button on the remote control.)
 <p>No Picture</p>	 <p>Normal Sound</p>	If a signal with a non-applicable colour system format, or frequency is input, only the input terminal indication is displayed.
 <p>No Colour</p>	 <p>Normal Sound</p>	Colour controls set at minimum level. Colour system (see page 26, 27)

## Plasma Display panel

Symptoms	Check
Some parts of the screen do not light up	The plasma display panel is manufactured using an extremely high level of precision technology, however, sometimes some parts of the screen may be missing picture elements or have luminous spots. This is not a malfunction.
 <p>After-images appear</p>	Do not allow a still picture to be displayed for an extended period, as this can cause a permanent after-image to remain on the Plasma Display. Examples of still pictures include logos, video games, computer images, teletext and images displayed in 4:3 mode.  <b>Note:</b> The permanent after-image on the Plasma Display resulting from fixed image use is not an operating defect and as such is not covered by the Warranty. This product is not designed to display fixed images for extended periods of time.
Whirring sounds can be heard from the display unit.	The display unit is fitted with a cooling fan to dissipate heat generated during normal use. The whirring sound is caused by rotation of the fan and is not a malfunction.

# Specifications

<b>TH-42PWD4</b>	
<b>Power Source</b>	220 - 240 V AC, 50/60 Hz
<b>Power Consumption</b>	
Normal use	295 W
Stand-by condition	1.8 W
Power off condition	1.6 W
<b>Plasma Display panel</b>	Drive method AC type 42-inch, 16:9 aspect ratio
Contrast Ratio	3000:1
Brightness Capability	(Panel only) 780 cd / m <sup>2</sup> (As a set) 400 cd / m <sup>2</sup>
<b>Screen size</b>	920 mm (W) × 518 mm (H) × 1056 mm (diagonal) No. of pixels 408,960 (852 (W) × 480 (H)) [2,556 × 480 dots]
<b>Operating condition</b>	
Temperature	0 °C - 40 °C
Humidity	20 % - 80 %
<b>Applicable signals</b>	
Colour System	NTSC, PAL, PAL60, SECAM, Modified NTSC
Scanning format	525i (480i), 625i (575i), 525p (480p), 625p (575p), 750p (720p), 1125/60i, 50i, 24p, 24SF (1080/60i, 50i, 24p, 24SF) ..... SMPTE 274M
PC signals	VGA display VGA SVGA, XGA, SXGA, UXGA (compressed) Horizontal scanning frequency 15.5 - 110 kHz Vertical scanning frequency 48 - 120 Hz
<b>Connection terminals</b>	
AV	Video IN (BNC) 1.0 Vp-p (75-ohm) S Video IN (MINI DIN 4PIN) Y: 1 Vp-p (75-ohm), C: 0.286 Vp-p (75-ohm) AUDIO IN (RCA PIN JACK × 2) 0.5 Vrms (high impedance) VIDEO OUT
COMPONENT/RGB	Y/G (BNC) 1.0 Vp-p/composite (75-ohm) 0.7 Vp-p/non-composite (75-ohm) P <sub>B</sub> /B (BNC) 0.7 Vp-p (75-ohm) P <sub>R</sub> /R (BNC) 0.7 Vp-p (75-ohm) HD (BNC) 1.0 - 5.0 Vp-p (high impedance) VD (BNC) 1.0 - 5.0 Vp-p (high impedance) AUDIO IN (RCA PIN JACK × 2) 0.5 Vrms (high impedance)
PC	(HIGH-DENSITY D-SUB 15PIN) R,G,B/0.7 Vp-p (75-ohm) HD, VD/1.0 - 5.0 Vp-p (high impedance) AUDIO IN (M3.5 JACK) 0.5 Vrms (high impedance)
SERIAL	EXTERNAL CONTROL TERMINAL (D-SUB 9PIN) RS-232C COMPATIBLE
SPEAKERS (6 Ω)	16W [8 W + 8 W] (10 % THD) For TY-SP42PWD3W only

<b>TH-42PWD4</b>	
<b>Accessories Supplied</b>	
Remote Control Transmitter	EUR646525
Batteries	2 × R6 Size
Fixing bands	TMME187 × 2
Ferrite core	J0KF00000018 × 2
<b>Optional Supplied</b>	
Speakers	TY-SP42PWD3W
Pedestal	TY-ST42PT3-K
Wall stand	TY-ST42PW1
Mobile stand	TY-ST42PF3
Wall-hanging bracket (vertical)	TY-WK42PV1
Wall-hanging bracket (angled)	TY-WK42PR1
Ceiling unit	TY-CE42PS1
Terminal Cover	TY-UPS200
<b>Dimensions (W × D × H)</b>	<p>1020mm × 610 mm × 89 mm</p>  <p>The drawing shows a rectangular unit with a width of 1020 mm and a depth of 610 mm. A side view shows a height of 89 mm.</p>
<b>Weight (Mass)</b>	<p>approx. 29.5 kg net (main unit only)</p> <p>approx. 33.7 kg (with speakers)</p>

**Notes:**

- (1) Design and specifications are subject to change without notice. Weight and dimensions shown are approximate.
- (2) This equipment complies with the EMC standards listed below.  
EN55022, EN61000-3-2, EN61000-3-3, EN61000-6-2.

**Customer' Record**

The model number and serial number of this product can be found on its back cover. You should note this serial number in the space provided below and retain this book, plus your purchase receipt, as a permanent record of your purchase to aid in identification in the event of theft or loss, and for Warranty Service purposes.

Model Number \_\_\_\_\_

Serial Number \_\_\_\_\_

---

**Matsushita Electric Industrial Co., Ltd.**Web Site : <http://www.panasonic.co.jp/global/>